

Oil is trapped in the bearing

Main Features

- Extremely Quiet
- Voltage Converter Cooling
- Patented Vibration Absorption
- Unique Cooling Performance
- Long Service Life
- 6 Heat Pipes
- Easy Installation
- 6 Years Warranty

Accelerator

Accelerator X1:

Compatible with:	Nvidia 6800 and 7800 series
Heat Sink:	152(L) x 90(W) x 30(H) mm
Fan:	141(L) x 120(W) x 28(H) mm
Fan Speed:	500 - 2000 RPM
Air Flow:	9.82 CFM / 16.7 m ³ /h
Bearing:	Fluid Dynamic Bearing
Weight:	262 g
Service Life:	MTTF at 40°C: 400'000 h
Cooling Performance (Thermal Resistance):	




Noise Level*:




Accelerator X2:

Compatible with:	ATI X1800 series and ATI X1900 series
Heat Sink:	152(L) x 90(W) x 30(H) mm
Fan:	141(L) x 120(W) x 28(H) mm
Fan Speed:	2000 RPM
Air Flow:	9.82 CFM / 16.7 m ³ /h
Bearing:	Fluid Dynamic Bearing
Weight:	260 g
Service Life:	MTTF at 40°C: 400'000 h
Cooling Performance (Thermal Resistance):	



Noise Level*:



*The noise level is measured in Sone (loudness) instead of dB (sound intensity). The loudness depends upon ears response curves and tells you exactly, how bothering a certain noise is.